

HASLER

WJ150 - Loading Rates Using Online Services

Introduction

When a new rate is announced by the USPS:


- An email notification is sent to the email address provided on your online profile about the pending rate change.
- A Generic Call must be performed to download the new rate.
- The rate update will not occur until the USPS effective rate change date.

Perform A Generic Call


Once an email notification about the pending rate change is received, a Generic Call must be performed to connect to the Online Services server to download the new rate.

- The mailing machine must be declared and covered by Total Rate Protection.
- If the mailing machine is not covered by Total Rate Protection, contact your authorized service provider to obtain the new rate package.

1. Press the **LOCK** button.



2. Press the **NEXT** button.




© 2009 Neopost USA Inc. All rights reserved.

No part of this document may be reproduced or distributed in any form or by any means without the express written permission of an authorized representative of Neopost USA. This document and all information contained herein are confidential and may only be disclosed as necessary to support customer use of the equipment.


Limitations of this Document

The information presented herein is subject to change. Neopost USA Inc. ASSUMES NO LIABILITY WHATSOEVER FOR ANY LOSSES OR DAMAGES RESULTING FROM USE OF THIS INFORMATION.


3. Press the **MENU** button.




4. Using the down arrow button, select **ONLINE SERVICES**.
- Press **OK**.




5. Using the down arrow button, select **GENERIC CALL**.
- Press **OK**.




6. The modem is initializing.



7. The mailing machine is connecting to the server.




8. The call completed successfully.




9. After the new rate loading is successfully completed, a message is sent to the Supervisor mailbox.

- Press **OK**.




10. Press the **HOME** button to return to the main screen.



New Rate Confirmation

To retrieve the message and confirm the new rate download, log into Supervisor mode.

1. Press the **SUPERV** button to access the Supervisor mode to retrieve the message.




2. Enter the Supervisor **PIN NUMBER, 9430**.

- Press **OK**.




3. Press the **MENU** button.




4. Using the down arrow button, select **ONLINE SERVICES**.

- Press **OK**



5. Using the down arrow button, select **MAILBOX SUPERVISOR**.


- Press **OK**.




6. The message in the mailbox will be displayed.

- Verify that the correct file, **#MHW10.01A**, has been downloaded.

- Press **ESCAPE** to close the mailbox.



7. Press the **HOME** button return to the main screen.



8. Press the **LOCK** button to put the machine to exit Supervisor mode and put the machine to sleep.

